

# MA onPC command wing



- Real-time control for 2,048 parameters in combination with grandMA2 onPC (up to 65,536 parameters as backup in the MA system)
- Command section similar to grandMA2 layout
- 2 A/B faders (100mm)
- 1 Level-Wheel
- Individually backlit and dimmable silent (clickless) keys
- Integrated universal power supply
- Ergonomic design

The MA onPC command wing paves the way for mobile use of the highly flexible and powerful grandMA2 control system. In combination with the free of charge grandMA2 onPC software, the MA onPC command wing is a portable 2,048 parameter control solution that can be used in nearly any location –and all for an affordable price.

Designed as the perfect hardware expansion to the grandMA2 onPC software, the MA onPC command wing enables the look and feel of the software to be as close to a real grandMA2 console as possible. Thanks to the MA onPC command wing – incorporating the command section of the grandMA2 consoles – it has never been easier to use the grandMA2 onPC software. With a simple USB connection between the MA onPC command wing and the computer running the grandMA2 onPC software, all inputs and outputs of a grandMA2 console are available to the user. DMX, Midi, Timecode and Analogue Remote are all on hand directly at the MA onPC command wing.

Wherever it is physically difficult to use a grandMA2 console, the MA onPC command wing, in conjunction with the grandMA2 onPC software, enables the customer to program or playback within the grandMA2 world. Therefore the MA onPC command wing is ideal to be used as a backup solution within the grandMA2 system, as powerful control solution on the road or for smaller theatres, shows and clubs or for preprogramming.

Furthermore it is possible to expand your parameter count. Below you can find all possible combinations and how many parameters you'll get out of them. There are two simple rules to regard.

First, MA 2Port Node onPC only count once and only the one with the most parameters is added. Means if you add a second MA 2Port Node onPC you won't get more parameters yet additional DMX connectors.

Second, the maximum parameter count with grandMA2 onPC is 4,096 parameters.

# MA onPC command wing

These combinations are possible:

grandMA2 onPC + MA onPC command wing = 2,048 parameters

grandMA2 onPC + MA onPC command wing + MA 2Port Node onPC = 2,560 parameters

grandMA2 onPC + MA onPC command wing + MA 2Port Node onPC PRO = 3,072 parameters

## Ordering Options

120120 MA onPC command wing

120134 MA onPC command wing bag

## Scope of delivery

Dust cover, USB cable 1.9m, power cord 1.9m IEC Plug (lockable) / open end

## Weight and Dimensions

21,5 x 15,6 x 2,8 inch - 546 x 395 x 70mm

6kg - 6kg