



The APart E-VOL60 is a 100Volt volume control. It is available in white and black color, and can handle up to 60 Watt of power.

It is very versatile thanks to the step-by-step attenuation in 11 steps + zero position.

The E-VOL 60 is designed to handle 24V priority signals. This means that you can always get an announcement out, even to zones where the local volume control is in the 'OFF' position!

If your amplifier has a 24 V priority output, it will send a 24 V signal when you push the talk button on the microphone. The 24 V signal will close a relay on the E-VOL60 volume control, and the signal will pass, even when the volume control is in the 'OFF' position. This can be very useful for emergency or evacuation messages.

The E-VOL60 is built on a universal chassis that easily can be integrated with Gira, Jung and Euro. Different cover plates are available for the UK market.

TECHNICAL SPECIFICATIONS

Type	Euro
Handling Power	60 Watt
Voltage	100 Volt
24 V priority	Yes
Attenuation steps	11 + "0"
Build-in box	E-MODIN
Build-on box	E-MODON
Dimensions (HxWxD)	80 x 80 x 50 mm
Weight	236 grams
color	E-VOL60 : white
also available as	E-VOL60-BL : black