LIVE-6

B08403

DESCRIPTION

Versatile PA mixer in a handy compact format, 6 inputs / 4 channels

FEATURES

- Versatile PA mixer in a handy compact format.
- Powered by a 5V USB connector.
- Combine it with a power bank and battery powered speakers to be 100% mobile.
- 6 inputs over 4 channels (2 mic/line, 1 mono/stereo line, 1 mono/stereo line /USB/player).
- The USB connector on the top panel is Bidirectional (for mono recording or stereo playback via PC/Mac).
- Internal WMA, WAV, FLAC, APE and MP3 media player for USB memory sticks.
- The media player can also be used as a mono mp3 recorder (128kbps).
- Integrated Bluetooth receiver.
- Internal 32bit DSP-effect unit with 99 effect variations.
- Input control on all the MONO channels:
 - Individual 48V Phantom Power switch on each mono channel!
 - -20dB PAD switch
 - Gain
 - Pan
 - Low Cut filter switch
 - Treble, semi-parametric mid, bass
 - Effect send
 - Channel level fader
- Balanced Master output.
- Headphones + control room output with level control.









TECHNICAL SPECIFICATIONS

General: Dimensions (cm) $25(W) \times 28(D) \times 6(H)$

General: Weight (kg) 1.8 **General: Powerinput** USB 5Vdc **General : Energy Label** No **General: Power consumption W** 5 **General**: Color black **General**: Display No **General: RU** No Audio: min. frequency (Hz) 20

Audio: max. frequency (Hz) **Audio: supported audio formats** APE, FLAC, MP3, WAV, WMA

20000

Audio: supported audio media

Audio: functions equalizer, sound effects 3 pin XLR, rca, jack, usb, **Connections: input** bluetooth

Connections: output 3 pin XLR, rca, jack, usb

Brand JB SYSTEMS **EANCode** 5420025684033







